

MFS- MCP



PRODUCT OVERVIEW :-

Conventional manual call point (MCP) is an emergency alerting device which can be activated by pressing a transparent plastic window on its front side. The call point once activated can be reset by pressing **Reset**. It is designed to use with conventional fire alarm control panel and alarm loop by installing the module conventional zone module. The zone module allows the fire alarm control panel to monitor the conventional call point devices.

OPERATION:-

1.PRESS HERE Key :-

MCP's are connected to the particular zone of conventional panel . In normal condition MCP's are blink after few sec.If "**Press here**" key press ,the MCP goes in fire condition, LED on MCP will ON and the particular zone number will display on conventional Panel .

2.RESET Key :-

It will **RESET** the Whole System.



ELECTRICAL SPECIFICATIONS:-

Resatable	YES. (Glass Replacement not Required)
Maximum Charge Current	0.6mA
Input Supply	24V DC

MECHANICAL SPECIFICATIONS:-

Material	Fire proof ABS
Colour	RED
Mounting	Wall Mounted
Dimensions	Approx. L 95 x H 95 x W 53mm
Temperature	5 C to + 40°C
Humidity	0 to 95 % Relative Humidity, Non Condensing GENERAL
Weight	100Gms

WIRING DAIGRAM:-

